SSD222
Smart Display CAM Controller

Preliminary Product Brief

FEATURES

- High Performance Processor Core
  - ARM Cortex-A7 Dual Core up to 1 GHz
  - 16KB I-Cache/16KB D-Cache/128KB L2-Cache
  - Neon and FPU
  - Memory Management Unit for Linux support
  - DMA Engine
- Image/Video Processor
  - Supports 8/10-bit parallel interface for raw data input
  - Supports max. two MIPI interfaces with 2 or 1 data lane and 2 clock lanes, up to 1.5GHz
  - Supports 8/10-bit BT.601/656 parallel interface
  - ISP processing performance up to 1920x1080p30
  - Bad pixel compensation
  - Temporal-domain Noise Reduction (3DNR)
  - Bayer domain Spatial-domain Noise Reduction (2DNR)
  - Bayer domain filter to remove purple false color in highlight regions
  - Optical black correction
  - Lens shading compensation
  - Auto White Balance (AWB) / Auto Exposure (AE) / Auto Focus (AF)
  - CFA color interpolation
  - Color correction
  - Gamma correction
  - Video stabilization
  - Frame buffer data compression and de-compression to save memory bandwidth
  - Wide Dynamic Range (WDR) with local tone mapping
- JPEG Encoder
  - Supports JPEG baseline encoding
  - Supports YUV422 or YUV420 formats
  - Supports max. resolution 720p (1280x720) with 30fps
- Display Subsystem
  - Built-in contrast, brightness, sharpness, and saturation, 3D NR, Gamma control
  - TTL output up to 1280x800 60fps with RGB565 or RGB666 or RGB888 format
  - BT.656 output up to 720p60
  - Serial RGB up to 800x600 60fps
  - Supports SPI panel, clock frequency up to 54MHz
  - Supports FHD graphic layer with Index 4/8, ARGB1555/ARGB4444/ARGB8888, and RGB565 format
  - Supports UI/OSD layer with max. resolution 1280x800
- 2D Graphics Engine
  - Line draw
  - Rectangle/gradient rectangle fill
  - Bitblt/Stretch Bitblt/Italic Bitblt
  - Palette mode (1/2/4/8-bit)
  - Format transformation
  - Color space conversion
  - Clipping
  - Alpha blending
  - Rotation/Mirror
  - Dither
- Audio Processor
  - Three mono ADCs or one mono + one stereo ADC for microphone input
  - Two stereo DMIC inputs
  - I2S TDM 8-channel, RX 2/4/8 channels, TX 2 channels
  - One stereo DAC for lineout
  - One HP Driver headphone set
  - I2S supports 8K/16K/32K/48K/96KHz sampling rate audio recording
  - ADC Pre-Amp gain supports 0dB, 6dB, 13dB, 23dB, 30dB, and 36dB
  - ADC boost gain supports -6dB ~ 15dB or 0dB ~ 21dB with interval 3dB
  - ADC digital gain supports -63.5dB ~ 33dB with interval 0.5dB, can be muted to zero
  - SNR of DR A-Weighted ADC > 90dB (@gain = 0dB)

- NOR/NAND Flash Interface
  - Supports 1/2/4-bit SPI-NOR / NAND flash with two chip selects
- SDIO 2.0 Interface
  - Compatible with SDIO spec. 2.0, data bus 1/4 bit mode
  - Compatible with SD spec. 2.0, data bus 1/4 bit mode
- USB 2.0 Interface
  - One USB2.0 configurable host and device
    - Host mode supports EHCI specification
    - Device mode supports 4 end points
- DRAM Memory
  - Supports 16-bit 512Mb DDR2 memory with max. 1333Mbps
  - Supports auto-refresh and self-refresh mode
- Ethernet
  - Supports one Ethernet port
  - Supports 10/100Mbps half/full-duplex
  - One built-in 10/100M Ethernet PHY
  - Supports one RMII to connect external PHY
  - Supports two LEDs for ePHY
- Security Engines
  - Supports AES/DES/3DES/RSA/SHA-I/SHA-256
  - Supports secure booting
- Boot options
  - ROM
  - SPI NOR
  - SPI NAND with ECC
  - SD Card and USB
- Peripherals
  - Dedicated GPIOs for system control
  - Four PWM outputs
  - Three generic UARTs and one fast UART with flow control
  - Three generic timers and one watchdog timer
  - Two SPI masters
  - Two I2C masters
  - Keypad supports up to 7x7, single mode
- Miscellaneous
  - Built-in eFuse with 1024-bit to store device ID, AES key, chip configurations, etc.
  - Built-in power on reset (POR)
  - Built-in SAR ADC with 3-channel analog inputs for different kinds of applications
- Operating Voltage Range
  - Core: 0.9V
  - I/O: 1.8V ~ 3.3V
  - DRAM: 1.8V (DDR2)
  - Power Consumption: TBD.
  - Operation temperature -20°C ~ 85°C
- Package
  - 128-pin QFN, 12.3mm x 12.3mm

BLOCK DIAGRAM



GENERAL DESCRIPTION

The SSD222 is a highly integrated SOC product for face access and smart display applications.

Based on ARM Cortex-A7 dual-core, the SSD222 integrates image sensor interface, advanced ISP, high performance JPEG encoder, 2D graphics engine, TTL/serial RGB display with adjustable picture quality engine and other useful peripherals.

A typical utilization of the SSD222 application processor is demonstrated in the block diagram. The completed system includes NOR/NAND flash, DRAM, SD card, and USB port, and diversified audio connection. Before output to the panel, the images can be enhanced with respect to brightness/contrast/saturation/sharpness to give the best picture quality.

The NOR or NAND flash is usually reserved for operating system and application software. Moreover, other peripherals like SAR ADC, Audio ADC/DAC, UARTs, PWMs, GPIOs and SPI are supported to realize applications with maximal flexibility.

The SSD222 supports secure booting and personalization authentication mechanism for securing system. The AES/DES/3DES cipher engines could also help encrypt the compressed video/audio streams for privacy protection.

The SSD222, powered by SigmaStar Technology, comes with a complete hardware platform and software SDK, allowing customers to speed up "Time-to-Market."